

## DALI WALL PLATE DIMMER



The Diginet DALI Wall Plate Dimmer brings together the simplicity of a dimmer on the wall and the sophistication of DALI controlled lighting. A built-in DALI bus power supply and capacity to control up to 50 DALI drivers with no PC programming required make it a cost effective, simple to install and easy to use solution for dimming DALI-based light fixtures.

Simple, on-wall control for DALI based light fixtures with Push for on/off and Rotate to dim up/down

Pocket sized power with a built in 125mA DALI power supply (mains connection required)

Colour Temperature control for DALI Type 8 (tunable) luminaires

Configurable minimum brightness setting

On board DALI power supply enabling control for up to 50 DALI devices

Multiple dimmer units can be connected in parallel to a DALI line for multi-point control

Designed to fit the Australian standard wall switch plate

No PC programming or software required

# DALI WALL PLATE DIMMER

## Product Specification

<b>IP20</b> Ingress Protection Rating	<b>2.3W</b> System Power	<b>240V</b> Voltage	<b>50Hz/60Hz</b> Line Voltage Frequency	<b>L120 x W75 x H53</b> Dimensions
<b>0 - 50</b> Operating Temperature	<b>53 x 75 x 120</b> dimensions			

Item Code	Description	Controls Interface	Dimming Technology
DGDALIDM	DALI WALL PLATE DIMMER	DALI SWITCH	DALI
DGDALIDM8	DALI TYPE 8 WALL PLATE DIMMER WHITE	DALI8 SWITCH	DALI8